

Garage Door Opener Comparison Chart



POWERED BY myQ



SERIES	Premium				Plus	Basic	
	Quietest. Most Powerful.		The Ultimate Garage Experience.		Everyday Convenience. Smart Control.	Simple. Smart. Dependable.	
Model Number	98032	98022	4690L	6690L	6580L	2420L	2220L
Previous Model	-	8500W, 8500, 8500C	87802, 85870	87504-267	84602, 84505R, 84504R, 83650-267, 81550	81602	81600, 81650
Description	DC Battery Backup Wall Mount Wi-Fi Lifts doors 400-1,100 lbs.	DC Battery Backup Wall Mount Wi-Fi Lifts doors up to 850 lbs.	Heavy-Duty DC LED Battery Backup Chain Drive Wi-Fi with Integrated Camera	1-1/4 HPs* DC LED Battery Backup Belt Drive Wi-Fi with Integrated Camera	1 HPs* DC LED Battery Backup Belt Drive Wi-Fi with Integrated Camera	DC Battery Backup Chain Drive Wi-Fi with Integrated Camera	DC Chain Drive Wi-Fi with Integrated Camera
Built-In Wi-Fi with Bluetooth®	Yes	Yes	Yes	Yes	Yes	Yes	Yes
myQ® Connectivity	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Integrated Camera	-	-	Yes - 360 swivel	Yes - 360 swivel	Yes - 360 swivel	Yes	Yes
California SB-969 Compliant**	Yes	Yes	Yes	Yes	Yes	Yes	-
Security+ 2.0®	Yes	Yes	-	-	-	-	-
Security+ 3.0®	-	-	Yes	Yes	Yes	Yes	Yes
Battery Backup*	Yes 2 485LM Batteries	Yes 485LM Battery	Yes 485LM Battery	Yes 485LM Battery	Yes 485LM Battery	Yes 485LM Battery	-
Garage Door Lock	841LM Automatic Garage Door Lock, 1 Included (2 Max.)	841LM Automatic Garage Door Lock, 1 Included (2 Max.)	-	-	-	-	-
Lighting	837LM myQ Remote LED Light, 1,000 Lumens	837LM myQ Remote LED Light, 1,000 Lumens	LED Light Ring, 2,000 Lumens	LED Light Ring, 2,000 Lumens	Dual LED Lighting System, 1,500 Lumens	1 LED Bulb (60 Watt Max)***	1 LED Bulb (60 Watt Max)***
Soft Start/Stop	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Rail	None	None	I-Beam Rail System, Sensor Extension Brackets, Chassis Support Bracket	T-Rail System	T-Rail System	T-Rail System	T-Rail System
Control Panel	880LMW Smart Control Panel	880LMW Smart Control Panel	L958W Smart Control Panel	L958W Smart Control Panel	L957W Motion-Detecting Control Panel	L955W Multi-Function Control Panel	L955W Multi-Function Control Panel
Motion Detection Light Activation	Yes	Yes	Yes	Yes	Yes	-	-
LCD Programming Menu	Yes	Yes	Yes	Yes	-	-	-
Light and Lock Functions	Yes	Yes	Yes	Yes	Yes	Yes	Yes
myQ Diagnostics	Yes	Yes	Yes	Yes	Yes	Yes	Yes
Pack-In Accessory	893MAX 3-Button Remote Control	893MAX 3-Button Remote Control	2 L993M 3-Button Remote Controls	2 L993M 3-Button Remote Controls, L979M Wireless Keyless Entry	L993M 3-Button Remote Controls	L993S 3-Button Remote Control	L993S 3-Button Remote Control
Accessory Capacity	40 Remote Controls, 4 Wireless Keyless Entries, 2 Automatic Garage Door Locks, 16 - 837LM Remote Work Lights	40 Remote Controls, 4 Wireless Keyless Entries, 2 Automatic Garage Door Locks, 16 - 837LM Remote Work Lights	16 Remote Controls, 3 Wireless Keyless Entries 2 Control Panels	16 Remote Controls, 3 Wireless Keyless Entries 2 Control Panels	16 Remote Controls, 3 Wireless Keyless Entries 2 Control Panels	16 Remote Controls, 3 Wireless Keyless Entries 2 Control Panels	16 Remote Controls, 3 Wireless Keyless Entries 2 Control Panels
Motor Warranty	Lifetime	Lifetime	Lifetime	Lifetime	6 Years	5 Years	5 Years
Parts Warranty	5 Years	5 Years	5 Years	5 Years	1 Year	1 Year	1 Year
Other Warranty	1 - Year Battery	1 - Year Battery	1-Year Battery, 5-Year LED, 1-Year Camera	1-Year Battery, 5-Year LED, 1-Year Camera	6-Year Belt, 1-Year Battery, 1-Year LED, 1-Year Camera	1-Year Battery	1-Year Battery
Replacement Logic Board	050DCRJJB3MC	041DJ003MC	030DCT	030DCT	030DCT	030DCT	030DCT
Openers per Pallet	18	24	40	40	44	40	40
Rail Part Numbers	-	-	3707CH, 3708CH, 3710CH, 3712RV, 3714RV	2777, 2778, 2770	2777, 2778, 2770	1707, 1708, 1710	1707, 1708, 1710

*For comparison purposes only; lift capacity similar to 1-1/4 or 1 horsepower AC motor. Lift capacity of DC motors is typically not measured in horsepower.

** According to California SB-969, all newly sold or installed garage door openers in residential applications in California need to have battery backup beginning July 1, 2019.

*** LED bulb not included

©2025 Chamberlain Group LLC. All Rights Reserved. LiftMaster, the LiftMaster logo, myQ and the myQ logo are registered trademarks of Chamberlain Group LLC. 300 Windsor Drive, Oak Brook, IL 60523 LiftMaster.com Wi-Fi® is a registered trademark of Wi-Fi Alliance. The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by The Chamberlain Group is under license.

Receiver Logic Board Conversion List



OPENERS BUILT FROM 1997-2005 390 MHz SECURITY+® WITH RED/ORANGE LEARN BUTTON						
MANUFACTURING DATE	DELUXE-CHAIN DRIVE	STANDARD-CHAIN DRIVE	CHAMBERLAIN® SCREW DRIVE	LIFTMASTER® SCREW DRIVE	BELT DRIVE	LIFTMASTER LOW-PROFILE SCREW DRIVE
1997 - 2005	41A5021 041A5021-(B-I) 41A5021-I	41A5021-1 041A5021-1(B-I) 41A5021-1I	41D4674-14 041D4674-14(D-H) 41D4674-20	41D4674-10 041D4674-10(C-H) 41D4764-20	41A5021-D 041A5021-5(E-I) 41A5021-5I	41A5839-1 041A5839-1(C-E)
IF YOU HAVE A BOARD ON THE LIST ABOVE, REPLACE IT WITH:						
	DISCONTINUED	DISCONTINUED	DISCONTINUED	DISCONTINUED	DISCONTINUED	DISCONTINUED

OPENERS BUILT FROM 2001-2005 390 MHz SECURITY+ WITH RED / ORANGE LEARN BUTTON						
MANUFACTURING	CHAIN DRIVE DELUXE END PANEL	CHAIN DRIVE STANDARD END PANEL	AC BELT DRIVE	AC CHAIN DRIVE DELUXE END PANEL DUAL CAPACITOR	DC BELT DRIVE WITHOUT BATTERY BACKUP	DC BELT DRIVE WITH BATTERY BACKUP
2001-2005	41A5483 41A5483B 041A5483C	41A5483-1 41A5483-1B 041A5483-1C	41A5483-4 41A5483-4B 041A5483-4C	41A5635 01A5635A	41A5507 41A5507B 041A5507-B	41A5507-3 41A5507-6 041A5507-6C
IF YOU HAVE A BOARD ON THE LIST ABOVE, REPLACE IT WITH:						
	DISCONTINUED	DISCONTINUED	DISCONTINUED	DISCONTINUED	DISCONTINUED	DISCONTINUED

OPENERS BUILT FROM 2005-2014 315 MHz SECURITY+ WITH PURPLE LEARN BUTTON						
MANUFACTURING DATE	AC CHAIN DRIVE DELUXE END PANEL	AC CHAIN DRIVE STANDARD END PANEL	CHAIN DRIVE DELUXE END PANEL DUAL CAPACITOR	CHAIN DRIVE DELUXE END PANEL SINGLE CAPACITOR	AC BELT DRIVE	DC BELT DRIVE LOW PROFI
2005-2014	41AC050 41AC050-2	41AC050-1	41AB075-2 41AC075-2 041AC075-2A	41AC075-2S	41AB050-2	41DB001-1
IF YOU HAVE A BOARD ON THE LIST ABOVE, REPLACE IT WITH:						
	041AC050-2M	041AC050-1M	DISCONTINUED	041AC075-2S	041AB050-2M	041DB001-1C

OPENERS BUILT FROM 2005-2014 315 MHz SECURITY+ WITH PURPLE LEARN BUTTON						
MANUFACTURING DATE	DC BELT DRIVE	DC SCREW DRIVE	WALL MOUNT MODEL 3800	AC SCREW DRIVE STANDARD	AC SCREW DRIVE LOW PROFILE	AC SCREW DRIVE DELUXE
2005-2014	41DB001-2	41DS002-2	41DJ001	41AS050 41AS050-1	41AS050R1	41AS050R2
IF YOU HAVE A BOARD ON THE LIST ABOVE, REPLACE IT WITH:						
	DISCONTINUED	DISCONTINUED	041DJ001B	041AS050-1	041AS050R1M	041AS050R2M

OPENERS BUILT FROM 2011-2021 310/315/390 MHz WITH YELLOW LEARN BUTTON									
MANUFACTURING DATE	DC CHAIN & BELT DRIVE	AC CHAIN & BELT DRIVE	AC CHAIN & BELT DRIVE NO myQ®	DC CHAIN & BELT DRIVE WI-FI®	AC CHAIN & BELT DRIVE WI-FI	DC CHAIN & BELT DRIVE WI-FI LOCK	AC CHAIN & BELT DRIVE WI-FI LOCK	DC BATTERY BACKUP WALL MOUNT WI-FI (8500W)	BATTERY BACKUP CAPABLE WALL MOUNT (8500)
2011-2023	45DCBL(1-5) 45DCCL(1-5) 45DCBR(1-5) 45DCCR(1-5) 45DCT 045DCT 041D7356	45ACBL(1-5) 45ACCL(1-5) 45ACBR(1-5) 45ACCR(1-5) 45ACT 041D7675 045ACT	47DCCR1 47DCCC1 47DCCL1 47DCT 047DCT 41D8060 1D8060 047DCT	50DCBL(1-5) 50DCCL(1-5) 50DCBR(1-5) 50DCCR(1-5) 1D8169-1 (1-2) 050DCTWF 050DCTBMC 050DCTB	50ACBL(1-5) 50ACCL(1-5) 50ACBR(1-5) 50ACCR(1-5) 1D8088-1 050ACTWF 041D8088 050ACTWFMC	50DCBL(1-5) I 50DCCL(1-5)LK 50DCTWFLK 050DCTWFLK 050DCTBLK 050DCTBLKMC	50ACBL(1-5)LK 50ACCL(1-5)LK 050ACTWFLK 50ACTWFLK	050DCRJWF	041DJ002
IF YOU HAVE A BOARD ON THE LIST ABOVE, REPLACE IT WITH:									
	045DCTMC	045ACTMC	DISCONTINUED	050DCTBFMC	050ACTBMC	050DCTBFLKMC	050ACTWFLKMC	050DCRJWFMC	041DJ002MC
OPENERS BUILT FROM 2022-2025 (315 MHz ONLY WITH ALTERNATE 390 MHz OPTION) WITH YELLOW LEARN BUTTON									
2022-2025	NA	045ACT	NA	050DCTBMC	050ACTBMC	050DCTBLKMC	050ACTBLKMC	050DCRJWFMC	041DJ002MC
OPENERS BUILT FROM 2025 - PRESENT (SECURITY+ 3.0) WITH WHITE LEARN BUTTON									
2025	NA	NA	NA	030DCT	NA	NA	NA	NA	NA